

BF 395	Si-N	AM/FM-V/M/O/ZF, >80MHz	7f	BF 255	7d	
BF 397	Si-P	Nix, Vid, 90V, 0,1A, 0,625W	7a	BF 421 A	7c	
BF 398	Si-P	=BF 397: 150V	7a	BF 421 A	7c	
BF 400	Si-P	VHF, >700MHz	8d	-		
BF 402	Si-P	VHF, >400MHz	8a	BF 324	7a	
BF 403	Si-N	SMD, NF, 30V 0,05A, 300MHz	35d(2mm)	-		
BF 404	Si-P	SMD, NF, 30V 0,05A, 150MHz	35d(2mm)	-		
BF 405	Si-N	SMD, NF, 45V 0,5A, >150MHz	35d(2mm)	-		
BF 406	Si-P	SMD, NF, 45V 0,5A, >150MHz	35d(2mm)	-		
BF 410	N-FET	VHF-ra, 20V, Idss>0,3mA, Up=1,5V	7f	-		
BF 411	Si-N	Nix, 110V, 0,05A, 0,3W, 120MHz	7a	BF 420 A	7c	
BF 412	Si-N	=BF 411: 150V	7a	BF 420 A	7c	
BF 413	Si-N	=BF 411: 200V	7a	BF 420 A	7c	
BF 414	Si-P	FM/VHF-V, 400MHz	7a	BF 324	7a	
BF 415	Si-N	Vid-L, 250V, 0,2A, 6W, >50MHz	14h	BF 471	14h	
BF 416	Si-P	Vid-L, 250V, 0,2A, 6W, >50MHz	14h	BF 472	14h	
BF 417(G)	Si-N	=BF 415: 300V	14h	BF 471	14h	
BF 418(G)	Si-P	=BF 416: 300V	14h	BF 472	14h	
BF 419	Si-N	Vid-L, TV-HA-Tr, 300V, 0,1A, 6W(Tc=90°)	14h	BF 459	14h	
BF 420(S)	Si-N	Vid, 300V, 25...50mA, 0,83W, >60MHz	7c	BF 420 A	7c	
BF 420 A	Si-N	=BF 420: 0,5A, 0,8W	7c	BF 420 A	7c	
BF 420 L	Si-N	=BF 420: 0,5A, 0,625W	7e	BF 420 A	7c	
BF 420 P	Si-N	=BF 420: 0,9W	30a	MPSU 10	13m	6
BF 420 P3	Si-N	=BF 420: 0,9W	30c	BF 759	13h	6
BF 421(S)	Si-P	Vid, 300V, 25...50mA, 0,83W, >60MHz	7c	BF 421 A	7c	
BF 421 A	Si-P	=BF 421: 0,5A, 0,8W	7c	BF 421 A	7c	
BF 421 L	Si-P	=BF 421: 0,5A, 0,625W	7e	BF 421 A	7c	
BF 421 P	Si-P	=BF 421: 0,9W	30a	MPSU 60	13m	6
BF 421 P3	Si-P	=BF 421: 0,9W	30c	-		
BF 422(S)	Si-N	=BF 420: 250V	7c	BF 420 A	7c	
BF 422 A	Si-N	=BF 422: 0,5A, 0,8W	7c	BF 420 A	7c	
BF 422 L	Si-N	=BF 422: 0,5A, 0,625W	7e	BF 420 A	7c	
BF 422 P	Si-N	=BF 422: 0,9W	30a	MPSU 10	13m	6
BF 422 P3	Si-N	=BF 422: 0,9W	30c	BF 759	13h	6
BF 423(S)	Si-P	=BF 421: 250V	7c	BF 421 A	7c	
BF 423 A	Si-P	=BF 423: 0,5A, 0,8W	7c	BF 421 A	7c	
BF 423 L	Si-P	=BF 423: 0,5A, 0,625W	7e	BF 421 A	7c	
BF 423 P	Si-P	=BF 423: 0,9W	30a	MPSU 60	13m	6
BF 423 P3	Si-P	=BF 423: 0,9W	30c	BF 762	13h	6*
BF 424	Si-P	HF, 300MHz	7a	BF 324	7a	
BF 435	Si-P	Vid, 160V, 0,2A, 0,625W, >80MHz	7c	BF 421 A	7c	
BF 436	Si-P	=BF 435: 250V	7c	BF 421 A	7c	
BF 437	Si-P	=BF 435: 300V	7c	BF 421 A	7c	
BF 439	Si-P	UHF-M/O, >900MHz	5g	(BF 979(S))	24e	4
BF 440	Si-P	AM/FM, re, 250MHz	7d	BF 324	7a	
BF 441	Si-P	AM/FM, 250MHz	7d	BF 324	7a	
BF 450	Si-P	AM/FM, re, 375MHz	7d	BF 324	7a	
BF 451	Si-P	AM/FM, 325MHz	7d	BF 324	7a	
BF 454	Si-N	AM/FM-ZF, 400MHz	8d	BF 255	7d	
BF 455	Si-N	AM/FM-V/M/O, 400MHz	8d	BF 255	7d	
BF 456	Si-N	Vid-L, 160V, 0,1A, 7W, 90MHz	14h	BF 459	14h	
BF 457	Si-N	Vid-L, 160V, 0,1A, 10W(Tc=45°), 90MHz	14h	BF 459	14h	
BF 458	Si-N	=BF 457: 250V	14h	BF 459	14h	
BF 459	Si-N	=BF 457: 300V	14h	BF 459	14h	
BF 460	Si-N	Vid-L, 250V, 0,5A, 10W, >45MHz	13m	MPSU 10	13m	
BF 461	Si-N	=BF 460: 300V	13m	MPSU 10	13m	